Performers:

Erica Jennings vocals

Vee Diawara el. & ac. guitars, PC, vocals

Willux MC
Paulius bass
Vytis drums

PA system:

A first class phase coherent PA system of top brands (L-Acoustics, d&b, Meyer sound, JBL, Martin audio, Turbo sound or adequate) capable to produce 110 dB of clear, undistorted sound with enough headroom at FOH position.

The type of PA system has to be approved by the sound engineer of the band.

Where necessary in / out / delay fills are required.

The PA system has to be fully patched, checked and ready before the soundcheck.

Mixing console, dynamics, effects:

Preferably digital: Allen&Heath (iLive series), DiGiCo (SD series), Yamaha (PM5D, M7CL, DM2000), Soundcraft (Vi series),

Midas (Pro series) or adequate.

 $\textbf{Or analog:} \ \textbf{Midas, Allen\&Heath, Soundcraft, APB or adequate. 32 channels, PEQ, 8 aux, 8 groups, GEQ on 6 monitor outputs.}$

Adequate amount of dynamic effects (compressors, noise gates) and FX processors. Read paragraph FOH.

Mixing console must be positioned in the audience, in line with the centre of the stage, at the distance 15 - 30 meters (depending on size of venue) from PA system.

The type of FOH mixing desk has to be approved in advance with sound engineer of the band.

PLEASE NO Yamaha 01v96, Yamaha LS9, Soundcraft Si, Soundcraft GB series.

Monitors, IEM systems:

Quantity of monitors is in the paragraph Stage.

Proffessional concert monitors of top brands (L-Acoustics, d&b, Meyer sound, JBL VTX, Martin audio, Turbo sound or adequate).

Preferably with 15" speakers. *All monitors have to be of same manufacturer.*

In-ear systems - Sennheiser 2000 / ew300 G3 or Sure PSM 900 / 1000.

Quantity of monitors and IEM systems is in the paragraph Stage.

Backline:

Drums:

High quality Pro level drum set made by Gretch (Renown or higher), Yamaha (Birch, Recording), Tama (something from this millenium) with all screws in right places. **No Pearl EXP, please.**

- 1 x Bass drum 20" or 22", 1 x Rack tom 12", 1 x Floor tom 14", 1 x Floor tom 16". Clear G2's on toms, holders and legs.
- **1 x** Snare drum 14" x 6" or 14" x 6,5". Ludwig BB or another high quality snare made by Ludwig. Also could be Tama, Gretch or DW. Equiped with coated Evans ST or similar durable drum head.
- E rings or tone controls on all drums including snare.
- 1 x Bass drum pedal (Pearl Eliminator, Tama Iron Cobra or DW 5000).
- 1 x stable drum seat with screw hight adjustment (Pearl Roadster would be good).

Cymbals: 1 x hihat 14", 2 x crashes 18" and 20" (or 2 x 18" with different tonal properties), 1 x ride 20".

All cymbals medium or medium thin. Made by Sabian (AA or HHX), Paiste (2002, Giant Beat or Signature) or Zildjian (A).

Stands: 1 x for hihat, 3 x for cymbals, 1 x snare stand (Yamaha or similar).

Drum rug of proper size.

Guitars, bass. Guitar & bass amplifiers:

- ${\bf 1}$ ${\bf x}$ ${\bf 6}$ strings electro-acoustic guitar (Ovation or similar) + STRAP. ${\bf 1}$ ${\bf x}$ Hercules guitar stand.
- 1 x 6 strings electric guitar (Gibson SG, Gibson Les paul, Fender Telecaster) + STRAP. 1 x Hercules guitar stand.
- 1 x Marshall JCM 900 2000 + cabinet + FOOTSWITCH or 1 x Fender Twin amp + FOOTSWITCH or similar.
- 1 x electric bass (Musicman Stingray 5 strings, Warwick Rockbass Corvette 5 strings) + STRAP. 1 x Hercules guitar stand.
- 1 x Ampeg SVT2, SVT3, SVT4 Pro amplifier + 2 cabinets SVT 410 HE and SVT 15E or 2 x SVT 410 HE.

Input channel list

Ch.	Source	Mic/DI	Stands	Specials
nr.				71.2.2.2
1	BD in	Shure Beta 91A	Short boom	Insert - noise gate
2	BD out	Shure Beta 52A		Insert - noise gate
3	SN TOP	Shure Beta SM57	Short boom	
4	SN BOTTOM	Shure SM57	Short boom	
5	HIHAT	AKG C 451 B	Short boom	
6	RACK TOM	Seinnheiser e904		Insert - noise gate
7	FLOOR TOM 1	Seinnheiser e904		Insert - noise gate
8	FLOOR TOM 2	Seinnheiser e904		Insert - noise gate
9	OH (RIDE)	AKG C 451 B	Tall boom	
10	OH (CRASH)	AKG C 451 B	Tall boom	
11	BASS	di-box		Insert - compressor
12	EL. GUIT (Vee)	Shure SM57	Short boom	
13	AC. GUIT (Vee)	di-box		Insert - compressor
14	PC L			Bal. jack or di-box
15	PC R			Bal. jack or di-box
16	Click			Bal. jack or di-box
17	VOC Vee	UHF-R Shure 58 (wireless)	Tall boom	Insert - compressor
18	VOC Erica	UHF-R Shure 58 (wireless)		Insert - compressor
19	VOC Willux	UHF-R Shure 58 (wireless)		Insert - compressor
20	VOC SPLIT Vee			
21	VOC SPLIT Erica			
22	VOC SPLIT Willux			
23				
24				
25				
26				
27				
28	FX Snare plate			FX return
29	FX Drum hall			FX return
30	FX Vocal hall			FX return
31	FX Tap delay			FX return
32	TALKBACK	Any mic with on/off switch		

Vocal mics - DYNAMIC ONLY !!!

Output channel list

Cn.	Source	Destination	Monitors	IEM
nr.				
1	AUX	Vee	2	
2	AUX	Erica	1	
3	AUX	Willux	2	
4	AUX	Bassist	1	
5	AUX	Drummer (own headphones and amplifier)		
6	AUX	Erica's IEM		1
7	AUX	FX Snare plate		
8	AUX	FX Drum hall		
9	AUX	FX Vocal hall		
10	AUX	FX Tap delay		

Stage:

Di-boxes (BSS AR-133)	5
Monitors	6
IEM systems	1

FOH:

Mixing desk	1
Noise gates (Klark teknik, Drawmer, dBx)	5
Compressors (Klark teknik, Drawmer, dBx)	5
FX - reverbs, delay (TC, Lexicon). Can be two double engine devices.	4